

# Webshop - Dreambox sky antene kompjutori videonadzor alarmi VU+ B.net Total TV DigiTV Polaris

3M&ZB d.o.o. RIJEKA

## DISEqC/USUALS ROTOR Optibox/Amiko DM3800 (KOMPATIBILAN USUALS)

Cijena: Kn430.00 (ukljuèen PDV)



Motor je predviðen za satelitske antene velicine do 140 cm. Ima potpuno metalni prijenos te je posebno robusan. Koristi se za digitalne satelitske prijelnike koji podržavaju DiseqC 1.2 / Usuals protokol. Priključuje se na prijelnik putem koaksijalnog kabela, tj. jedan kraj kabela se priključuje na motor, a drugi na prijelnik. Motor ima 2 konektora tako da se drugi konektor spaja direktno na LNB. Kabel koji povezuje motor i prijelnik istovremeno napaja i LNB i motor. Karakterizira ga naèin postavljanja pošto se postavlja na antenski stup sa okrenutom rukom prema dole i time koristi silu zemljine teže prilikom spuštavanja motora u krajnji položaj lijevo ili desno.

Protocol DiSEqC 1.2 & Goto "X"

Compatible Receiver DiSEqC 1.2, USUALS or Interface Box

Antenna Size 100 cm Max (31 lbs)

Speed 1.9° / sec (at 13V) ; 2.5° / sec (at 18V)

Azimuth Angle 80° East ~ 80° West ( 160° )

Elevation Angle 25~75°

Input Voltage 13 / 18Vdc

Output Voltage 13 / 18Vdc

Power Consumption 50 mA (Standby)

200mA (Normal)

350mA (Max.)

Satellite Positions 60 positions

Calibration Function Yes ( Go to 0°)

Manual East/West Buttons Yes (Build-in on the bottom of the Mount)

Limit Protection 1.Fixed type with micro switches

2.Programmable Software Limit

3.Current Limit

Positioning Sensor High Resolution Hall Effect Sensor

Connector F-Type

Weight ( Mount ) 3.1 Kg (Net) / 3.5 Kg (Gross) (~ 8 lbs)

Dimension ( Mount ) 345 x 168 x 110 mm<sup>3</sup> (Gross)

[Informacije o dobavljaèu](#)